

MARSHALL MG SERIES POTENTIOMETER CHART																		
		G10mkl	G15RCD	G30RCD	G215RCD	G50RCD	G80RCD	G100RCD	B25	MG10CD	MG15CD	MG15CDR	MG15DFX	MG30DFX	MG50DFX	MG250DFX	MG100DFX	MG100HDFX
P-MGP-	B200K LIN 16MM		G, T,	T, OT	G, T	CG, T,	CG, OT	CG, OT										
P-MGP-	B5K LIN 16MM						CM	CM		OV	OV, T	OV, T, R	OV, T, DFX	DFX-A	DFX-L, DFX-A, R	DFX-L, DFX-A, R	MV, R, DFX-L, DFX-A	R, DFX-L, DFX-A
P-MGP-	B20K LIN 16MM		R, C	R, C	C	M, R, C	T, M	T, M						CT, OT	CT, OT	CT, OT	CT, OT	CT, OT
P-MGP-	B100K LIN 16MM				CS, V	V	C	C						OV	CG, OV	CG, OV	OV	OV
P-MGP-	A500KA LOG 16MM					OG												
P-MGP-	A1M LOG 16MM		B	B, V, OG, OB	B	B	OG, OB	OG, OB		OG	OG	OG	OG	OG	OG	OG	OG, CG	CV
P-MGP-	B10K LIN 16MM		V		V, CD		MV	MV							MV			
P-MGP-	A5K LOG 16mm									CV	CV, M	CV, M	CV, M		CM	CM	CM, OM	CM, OM
P-MGP-	A20K LOG 16mm										B	B	B	CB, OB	OB, CB	OB, CB	CB, OB	CB, OB
P-MGP-	C5K ALOG 16mm												DFX-L	DFX-L				MV
P-MGP-	C100K ALOG 16mm													C	C	C	C	C
P-MGP-	B10K LIN TANDEM 16mm															MV	LL	LL
P-MGP-	A100K LOG 16MM						CB, OV	CB, OV	B, M, T					CV				
P-MGP-	A10K LOG 16MM		MV															
P-MGP-	B50K LIN 16MM								V									
P-MGP-	A50K LOG 16MM	V, G, C								C								
P-MGP-	B1M LIN 16MM			OV														

KEY FOR ABBREVIATIONS	
V	VOLUME
G	GAIN
M	MIDDLE
T	TREBLE
B	BASS
R	REVERB
CS	CHORUS SPEED
CD	CHORUS DEPTH
MV	MASTER VOLUME
C	CONTOUR
CG	CLEAN GAIN
OG	OVERDRIVE GAIN
OB	OVERDRIVE BASS
OT	OVERDRIVE TREBLE
OV	OVERDRIVE VOLUME
DFX-L	DFX LEVEL
DFX-A	DFX ADJUST
CB	CLEAN BASS
CT	CLEAN TREBLE
CM	CLEAN MIDDLE
CV	CLEAN VOLUME
LL	LOOP LEVEL
CV	CLEAN VOLUME